



US007343579B2

(12) **United States Patent**
Coxe et al.

(10) **Patent No.:** **US 7,343,579 B2**
(45) **Date of Patent:** **Mar. 11, 2008**

(54) **RECONFIGURABLE ENVIRONMENTALLY
ADAPTIVE COMPUTING**

(75) Inventors: **Robin L. Coxe**, Boston, MA (US);
Gary E. Galica, Medford, MA (US)

(73) Assignee: **Physical Sciences**, Andover, MA (US)

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 297 days.

(21) Appl. No.: **10/999,463**

(22) Filed: **Nov. 30, 2004**

(65) **Prior Publication Data**

US 2006/0117164 A1 Jun. 1, 2006

(51) **Int. Cl.**

G06F 17/50 (2006.01)

G06F 11/00 (2006.01)

G01R 31/28 (2006.01)

(52) **U.S. Cl.** **716/16**; 714/3; 714/725

(58) **Field of Classification Search** 716/16-17;
455/84; 712/15, 226; 713/100; 714/2, 13,
714/25, 31, 42-43, 47, 54, 736, 762, 799,
714/725, 1, 3

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

6,072,994 A * 6/2000 Phillips et al. 455/84

6,157,875 A * 12/2000 Hedman et al. 701/1
6,175,940 B1 * 1/2001 Saunders 714/746
7,036,059 B1 * 4/2006 Carmichael et al. 714/725
2002/0157071 A1 * 10/2002 Schiefele et al. 716/6
2004/0199813 A1 * 10/2004 Hillman et al. 714/13
2004/0247075 A1 * 12/2004 Johnson et al. 378/57
2004/0256568 A1 * 12/2004 Sekine et al. 250/370.11
2005/0040844 A1 * 2/2005 Plants 326/9
2005/0078174 A1 * 4/2005 Casey et al. 348/61
2005/0193255 A1 * 9/2005 McCollum 714/30
2006/0020774 A1 * 1/2006 Ramos et al. 712/226

* cited by examiner

Primary Examiner—Paul Dinh


(74) *Attorney, Agent, or Firm*—Proskauer Rose LLP

(57) **ABSTRACT**

Described are methods and apparatus, including computer program products, for reconfigurable environmentally adaptive computing technology. An environmental signal representative of an external environmental condition is received. A processing configuration is automatically selected, based on the environmental signal, from a plurality of processing configurations. A reconfigurable processing element is reconfigured to operate according to the selected processing configuration. In some examples, the environmental condition is detected and the environmental signal is generated based on the detected condition.

31 Claims, 7 Drawing Sheets

100






FIG. 1





FIG. 2






FIG. 4

500




FIG. 5




FIG. 6




FIG. 7

1

RECONFIGURABLE ENVIRONMENTALLY ADAPTIVE COMPUTING

GOVERNMENT RIGHTS

The government may have certain rights in the invention under Contract No. F29601-02-C-0069 awarded by the United States Air Force and Contract No. NNA04CB32C awarded by NASA.

FIELD OF THE INVENTION

The present invention relates to reconfigurable environmentally adaptive computing.

BACKGROUND OF THE INVENTION

A reconfigurable processing device typically refers to an electronic device that can dynamically change its internal configuration during runtime to change the way input signals are processed. One example of such a device is a reconfigurable microprocessor. Another example of such a device is a reconfigurable field programmable gate array (FPGA). An FPGA is a form of programmable logic device (PLD) that includes of an array of logic that can be connected in a variety of ways to perform certain processing functions. Instead of being hardwired to operate in only one functional mode, a reconfigurable FPGA typically can be loaded with a configuration that defines how the logic is connected. A reconfigurable FPGA includes two types of functional elements: configurable interconnect logic and volatile memory (e.g., static random access memory (SRAM)), that stores the loaded configuration. In operation, the reconfigurable FPGA configures its programmable interconnect logic using the configuration data in the memory layer. When a new configuration is loaded into the memory layer, the reconfigurable FPGA reconfigures its programmable logic using the newly-loaded configuration.

Techniques have been described for monitoring the internal aspects of the reconfigurable FPGA for fault detection. For example, a technique involves continuously reading the volatile memory elements to verify that the configuration is not corrupted. Some techniques also include reconfiguring the FPGA when such an internal inspection discovers a fault in either the configurable logic element or the volatile memory element. See for example U.S. Pat. No. 6,526,559, which describes a method for creating circuit redundancy in programmable logic devices.

SUMMARY OF THE INVENTION

The description describes methods and apparatus, including computer program products, for reconfigurable environmentally adaptive computing. In general, in one aspect, there is an adaptive computing system. The adaptive computing system includes a detector, a controller element, and a processing element. The detector generates an environmental signal representative of an external environmental condition. The controller element receives the environmental signal from the detector and selects a processing configuration from a plurality of processing configurations based on the environmental signal. The processing element that reconfigures itself to operate in accordance with the selected processing configuration received from the controller.

In another aspect, there is a computer program product, tangibly embodied in an information carrier, for reconfig-

2

urable environmentally adaptive computing. The computer program product including instructions being operable to cause data processing apparatus to receive an environmental signal that represents an environmental condition external to the adaptive computing system, select a processing configuration from a plurality of processing configurations based on the environmental signal, and initiate the reconfiguring of a reconfigurable processing element to operate according to the selected processing configuration.

In another aspect, there is an adaptive computing system. The system includes a means for generating an environmental condition signal and a means for selecting a processing configuration from a plurality of processing configurations based on the environmental condition signal. The system also includes a means for reconfiguring a processing element to operate according to the selected processing configuration.

In another aspect, there is a method. The method includes receiving an environmental signal representative of an external environmental condition and selecting a processing configuration from a plurality of processing configurations based on the environmental signal. The method also includes reconfiguring a processing element to operate according to the selected processing configuration.

In other examples, any of the aspects can include one or more of the following features. The detector can include a sensor. The sensor can include a radiation detector. The radiation detector can include a scintillator and a photodiode. The sensor can include a location detector. The location detector can include a geographical positioning system sensor. The detector can include a single event upset detection circuit having a radiation detector. The detector can include a radiation detector and a location detector. The detector can include an image processing detection circuit. The environmental signal can be based on a characteristic of a processed image. The characteristic can include a particular feature within the processed image. The characteristic can include an unexpected feature within the processed image. The processing element can include a programmable logic device. The programmable logic device can include a field programmable gate array. The processing element can include a radiation-hardened programmable logic device. The environmental signal can be based on a characteristic of output data from the processing element. The processing element can accommodate high bandwidth applications.

The external environmental condition can be detected and the environmental signal can be generated based on the detected condition. The detecting can include detecting a radiation level. The processing configuration can be a first processing configuration. In such examples, an increase in the radiation level can be detected, and a second processing configuration that is more fault tolerant than the first processing configuration can be selected. Detecting can include detecting a position. Detecting can include detecting a particular condition within image data. Detecting can include detecting a particular feature within the image data. Detecting can include detecting an unexpected feature within the image data.

Implementations can realize one or more of the following advantages. A processing device can be reconfigured during runtime to operate based on the environment in which it operates, thus proactively preventing failures from occurring, instead of reacting to failures that have already occurred. As the environment changes, the reconfigurable processing device can reconfigure itself to adapt to the changing environment. This reconfiguration maximizes utilization of resources, as high performance, low power con-

figurations can be used whenever possible. As the environment becomes harsher, the reconfigurable processing unit can configure itself to a more reliable and redundant, higher power configuration, only while the harsh environment remains. The environment cannot always be predicted or modeled, so by adapting the configuration to the current environment, the reconfigurable processing device can react to unexpected changes. Continual human intervention is not needed to readjust for the different changing environments. One implementation of the invention provides at least one of the above advantages.

The details of one or more examples are set forth in the accompanying drawings and the description below. Further features, aspects, and advantages of the invention will become apparent from the description, the drawings, and the claims.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram of an exemplary reconfigurable environmentally adaptive computing system.

FIG. 2 is a block diagram of another exemplary reconfigurable environmentally adaptive computing system.

FIG. 3 is a block diagram of an exemplary process of reconfigurable environmentally adaptive computing.

FIG. 4 is a block diagram of an exemplary radiation detecting circuit.

FIG. 5 is a block diagram of an exemplary reconfigurable environmentally adaptive computing system for use in space.

FIG. 6 is a block diagram of an exemplary reconfigurable environmentally adaptive computing system with multiple inputs.

FIG. 7 is a block diagram of an exemplary reconfigurable environmentally adaptive computing system that processes image data.

DETAILED DESCRIPTION

FIG. 1 illustrates a system 100 that can be used for reconfigurable, environmentally adaptive computing. The system 100 includes a detector 105 to detect an environmental condition 110 external to the system 100. Examples of an external environmental condition 110 can include, for example, a physical location of the system 100, a level or change of level of radiation exposure by the system 100, an event being processed by the system 100 (e.g., images of a volcano erupting), characteristics in images being processed by the system 100 (e.g., particular spatial or facial features), characteristics in hyperspectral images being processed by the system 100 (e.g., particular wavelengths or wavelength bands), etc. The detector 105 generates a signal based on the environmental condition 110 and transmits that signal to a controller element 115. Based on that signal, the controller element 115 selects a processing configuration from the processing configurations stored in a storage module 120 (e.g., non-volatile memory). Different configurations can be defined based on factors such as throughput, energy efficiency, power consumption, redundancy, and fault tolerance.

The controller element 115 initiates the transfer of the selected configuration from storage module 120 to a reconfigurable processing element 125 (e.g., reconfigurable FPGA). Upon receipt of the configuration data, the reconfigurable processing element 125 reconfigures itself according to the received configuration. Once configured, the reconfigurable processing element 125 processes input data 130 according to the new configuration to produce the

output data 135. Some reconfigurable processing elements are partially reconfigurable, meaning that a portion of the programmable logic can be changed while another portion remains unchanged. This allows processing of data to continue in the unchanged portion while the changed portion is reconfigured. See, for example, the Virtex-II family of reconfigurable FPGAs manufactured by Xilinx, Inc. of San Jose, Calif.

As a simple example, the external environmental condition 110 can be the location of the system 100. For this example, the detector 105 includes a global positioning system (GPS) receiver that calculates an accurate position of the system 100. The detector 105 sends the coordinates representing the location of the system 100 to the controller element 115. The controller element 115 selects the configuration that corresponds to the location of system 100. For example, if the system 100 is recording images as it travels and is located at a location of interest, the controller element 115 selects a configuration to process the images in a high-resolution mode. When the system 100 moves out of the location of interest and the detector 105 transmits new location information, the controller element 115 selects a configuration to process images in a low resolution mode, thus advantageously conserving resources. The processing element 125 reconfigures itself and starts processing the images in a low-resolution mode.

FIG. 2 illustrates a system 200 that also can be used for reconfigurable, environmentally adaptive computing. The system 200 includes a reconfigurable FPGA 205, a scintillator 210, an avalanche photodiode 215, detection circuitry 220, a radiation-hardened controller 225 and a configuration programmable read-only memory (PROM) 230. In the system 200, the external environmental condition monitored is radiation exposure by the FPGA. The combination of the scintillator 210, the avalanche photodiode 215, and the detection circuitry 220 can collectively be a detector that is sometimes referred to as a single event upset (SEU) alarm 240. The SEU alarm 240 detects radiation events commonly associated with SEUs. SEUs commonly refer to transient errors in data and they are typically non-destructive to the hardware. According to the NASA thesaurus, single event upset (SEU) is radiation-induced errors in microelectronic circuits caused when charged particles (e.g., from the radiation belts or from cosmic rays) lose energy by ionizing the medium through which they pass, leaving behind a wake of electron-hole pairs. The SEU alarm 240 provides continuous monitoring of the proton and heavy-ion fluxes that cause single event upsets.

The illustrated example of the SEU Alarm 240 includes a small block of scintillator 210 coupled to the avalanche photodiode (APD) 215. The scintillator 210 and the avalanche photodiode (APD) 215 output an analog voltage proportional to either instantaneous flux or fluence of incident charged particles. The controller 225 receives the analog voltage from the APD 215 and sends warnings, via status lines, when the flux or fluence exceeds user-determined limits. In one example, the SEU alarm 220 approximately weighs 25 grams, occupies a volume of 10×10×30 mm³, and consumes 20 mW of power. In this example, the SEU alarm 240 is small enough to be placed directly over or beside the FPGA 205, thereby measuring the SEU-inducing environment in close proximity to the FPGA 205. When the SEU alarm 240 detects a potentially hazardous environment, the SEU alarm 240 sends an alarm signal to the controller 225. A finite state machine executing on the microcontroller 225 prompts the FPGA configuration PROM 230 to change the reconfiguration of the FPGA to one or more "robust"

5

processing modes by transmitting the stored configuration **240** to the FPGA **205**. When the environment returns to a benign state, the controller **225** automatically reconfigures the FPGA **205** back to a default “high throughput” mode.

FIG. **3** illustrates an exemplary process **300** of reconfigurable environmentally adaptive computing using, for example, the exemplary system **200**. The controller **225** receives (**305**) an environmental condition signal from the SEU alarm **235** indicating radiation exposure. In one example, the signal is a two bit signal, with the first bit indicating whether some minimum level of radiation is present and the second bit indicating whether a maximum threshold has been exceeded. The controller **225** determines (**310**) whether there is an indication of radiation. For example, using the two bit example, the controller reads the first bit, where a logic zero indicates that the minimum level has not been exceeded and a logic one indicates that the minimum level has been exceeded. If the controller **225** determines (**310**) that there is no indication of radiation (e.g., logic zero), then the controller **225** selects a configuration from configuration PROM **230** that represents a high performance, low power processing configuration, as the threat of a SEU is low. The configuration PROM **230** transmits the selected configuration to the FPGA **205** and the FPGA **205** reconfigures (**320**) itself according to the received configuration.

If the controller **225** determines (**310**) that there is an indication of radiation (e.g., logic one), then the controller **225** determines (**325**) whether the radiation has exceeded a maximum threshold. For example, using the two bit example, the controller reads the second bit, where a logic zero indicates that the maximum level has not been exceeded and a logic one indicates that the maximum level has been exceeded.

If the controller **225** determines (**325**) that the maximum level has not been exceeded (e.g., logic zero), then the controller **225** selects a configuration from configuration PROM **230** that represents a robust performance, medium power processing configuration, as the threat of a SEU is increasing. For example, a robust performance can include scrubbing the configuration bit stream and enabling partial reconfiguration of the FPGA **205**. The configuration PROM **230** transmits the selected configuration to the FPGA **205** and the FPGA **205** reconfigures (**320**) itself according to the received configuration. If the controller **225** determines (**325**) that the maximum level has been exceeded (e.g., logic one), then the controller **225** selects a configuration from configuration PROM **230** that represents an ultra-robust performance, high power processing configuration, as the threat of a SEU is high. For example, an ultra-robust performance can include scrubbing the configuration bit stream, enabling partial reconfiguration of the FPGA **205**, and using triple modular redundancy logic. The configuration PROM **230** transmits the selected configuration to the FPGA **205** and the FPGA **205** reconfigures (**320**) itself according to the received configuration.

Process **300** is a continuous loop, so that the controller **225** continuously monitors the environment and adapts the FPGA accordingly, using one of the stored configurations. To perform the continuous monitoring, the controller **225** can periodically query the detection circuitry **220** to obtain an updated environmental condition signal. In other examples, the environmental condition signal can be a voltage level (e.g., zero or five volts) on an input port of the controller **225** that is generated by the detection circuitry **220**. This continuous loop enables the system **200** to autonomously reconfigure the mode (e.g., normal, robust, or ultra-

6

robust) in which the FPGA **205** processes data based on the changing environmental conditions (e.g., amount of detected radiation). This autonomous mode switching is advantageous in many typical satellite orbits, such as low Earth orbit (LEO) polar orbits where satellites pass through the South Atlantic Anomaly, geostationary equatorial orbit (GEO) transfer orbits where the satellites traverse the radiation belts, and geosynchronous orbits where satellites are subjected to geomagnetic disturbances and solar proton events.

FIG. **4** illustrates another example of a SEU alarm **400**. The SEU alarm **400** includes a detector **405** (e.g., scintillator **410** and photodiode **415**), analog preamp and discriminator **420**, gated counter **425**, comparator **430**, and control module **435**. In some examples, the SEU alarm **400** can be manufactured using a combination of parts available from various vendors. Table 1 includes a list of components and examples of one or more vendor parts that can be used to implement that particular component.

TABLE 1

COMPONENT	VENDOR	PART NUMBER
Scintillator	Bicron	BC400 Plastic Scintillator
	Rexon	Yttrium Aluminum Perovskite scintillator
Photodiode	Hamamatsu	S3399 PIN photodiode
	Hamamatsu	C5331 Avalanche photodiode
	Hamamatsu	R7400 Photomultiplier tube
Analog Preamplifier	Amptek	A203 Charge-sensitive preamplifier
Counter	ADI	LF312 Operational amplifier
	Toshiba	74HC593 Digital counter

As described above, the scintillator **410** and the photodiode **410** of the detector **405** output an analog voltage proportional to either instantaneous flux or fluence of incident charged particles. The analog preamp and discriminator **420** receives this signal and amplifies the level (e.g., analog preamp portion), and screens any signals below a certain level (e.g., discriminator portion).

A user can set the screening level through the control module **435**. The control module **435** provides a linear energy transfer (LET) threshold signal **440** to the analog preamp and discriminator **420** to set the screening level. Linear energy transfer (LET) is a measure of the energy transferred to a device per unit length as an ionizing particle travels through a material and is typically measured in MeV-cm²/mg of material (Si for MOS devices). The LET threshold signal **440** allows the user to adjust the particle energy (or LET) that signifies a “SEU-relevant” particle. This threshold determines which particles are counted by the counter **425**. In one example, the LET threshold signal **440** is an 8 to 10 bit signal generated by the control module **435** with a magnitude of 0-5 volts, and an output impedance of less than or equal to 50 ohms. The user can set the level, for example, using a computing device in communication with the command input port **445** of the control module **435**. Alternatively, in a case where the control module **435** is not used, the SEU alarm **400** can include one or more switches that the user can set to adjust the LET threshold value.

Any signals from the detector **405** that represent particles with energy above the LET threshold are passed through the analog preamp and discriminator **420** to the counter **425**. The counter **425** counts the particles over a certain period. In other words, the number of particles over a period of time sets the flux level that is used to trigger an alarm condition. The counter **425** sets that period using a gate time signal **450**. A user can set the period through the control module **435** and

the control module **435** provides the gate time signal **450** to the counter **425**. In one example, the gate time signal **450** is a clock signal generated by the control module **435** with a rising edge that latches the counter **425** and starts a new integration period. The clock signal can have a one to 50 microseconds pulse width and a pulse separation time of one millisecond to 10 seconds. The user can set these parameters, for example, using a computing device in communication with the command input port **445** of the control module **435**. Alternatively, in a case where the control module **435** is not used, the SEU alarm **400** can include one or more switches that the user can set to adjust the period value.

The counter **425** outputs the state of the counter **425** to the comparator **430**. When the comparator **430** determines that the state of the counter **425** has exceeded a count threshold, the comparator **430** generates an output signal on an alarm line **455** indicating that the threshold has been exceeded. For example, the output signal on the alarm line **455** can be a zero volt signal (e.g., logic zero) to indicate that the threshold has not been exceeded and a five volt signal (e.g., logic one) to indicate that the threshold has been exceeded.

The control module **435** also includes some optional ports **460**, **465**, **470**, and **475**. The control module **435** uses port **460** to transmit a calibration pulse across a capacitor **480**. The control module **435** uses port **465** to transmit housekeeping telemetry to other systems that are monitoring parameters of the SEU alarm **400**. For example, some of the parameters that can be included in the housekeeping telemetry are the LET threshold signal **440** (or digital equivalent), the gate time signal **450** (or digital equivalent), the output signal of the counter **425**, the state of the alarm line signal **455**, the measured temperature of the system **400**, and spare data words for any additional signals. Ports **470** and **475** can be used to obtain the values of the output signal of the counter **425** and the state of the alarm line signal **455**, respectively. In one example, the control module **435** samples the housekeeping telemetry parameters at 0.1 Hz to 1 Hz, and outputs an 8 bit signal from port **465** at a rate of 4.8 to 48 bits per second. The power to control module **435** at port **480** can be +15V, -15V, and/or +5V.

The SEU alarm **400** outputs a single alarm line signal **455** (e.g., a single bit) to indicate whether a threshold has been passed. The process **300** described a multiple threshold scenario where there was an indication of both a minimum level exceeded and a maximum level exceeded (e.g., two bits). The SEU alarm **400** can be used in a variety of ways to implement a multiple level threshold scenario. In one example, multiple SEU alarms **400** can be used in parallel, with each being set at different threshold levels (e.g., using the user adjustable LET threshold signal **440** and/or the user adjustable gate time signal **450**). In another example, the housekeeping telemetry data output on port **465** can be used. For example, the output of the counter **425** can be used to indicate some minimum threshold has been exceeded (e.g., radiation detected), and then the alarm line signal **455** can be used to indicate a maximum threshold has been exceeded.

FIG. 5 illustrates a system **500** that can be used for reconfigurable, environmentally adaptive computing in space. The system **500** includes a fault management system **505** and a reconfigurable processing system **510**. The reconfigurable processing system **510** reconfigures itself based on a selected configuration **513** transmitted by the fault management system **505**. The fault management system **505** serves as the controlling element to select the configuration **513** from a group of predefined configurations for the reconfigurable processing system **510**. The fault manage-

ment system **505** selects the configuration **513** based on multiple inputs representing external environmental conditions **515**.

One input is from a detector **520**, which monitors system commands of the spacecraft in which system **500** resides. The system commands are commands originating from a user or autonomous mission control software. Any commands that are indicative of what is happening in the external environment can be used by the fault management system **505** to select a configuration and reconfigure the reconfigurable processing system **510** based on those environmental conditions. For example, the detector **520** can monitor commands for the environmental systems, such as temperature control, humidity control, airflow, etc. to determine the appropriate configuration for the appropriate environmental conditions. For example, the fault management system **505** can select a more redundant configuration in a high temperature environment, when the reconfigurable device is more prone to failures. When the temperature decreases again, the fault management system **505** can select a less redundant, higher performance, lower power configuration. The detector **520** can monitor commands from the navigation systems, such as commands for sudden changes in orbit that might be lead to more failure prone output data and again, select a more redundant configuration only when needed.

Another input is from a SEU detector **525** (e.g., a SEU alarm, such as **235** or **400**), which monitors SEU inducing particles **530** in the environment that might cause a SEU. As described in some of the examples above, output signals from the SEU detector **525** that are indicative of the external environment can be used by the fault management system **505** to select the configuration **513** and reconfigure the reconfigurable processing system **510** based on the environmental conditions.

Another input is from a detector **535**, which monitors the spacecraft ephemeris. Output signals from the spacecraft ephemeris detector **535** are indicative of the location of the spacecraft in its orbit and can be used by the fault management system **505** to select the configuration **513** and reconfigure the reconfigurable processing system **510** based on that location. The fault management system **505** can use the location data in a variety of ways. For example, certain locations may be more prone to cause faults because of different characteristics of that location (e.g., higher interference, higher noise, higher radiation, etc.). For these reasons, a higher reliability configuration can be selected based on that location. In other cases, particular locations may be of greater interest than other locations. For example, the reconfigurable processing element of the configuration system **510** is processing image data and previously at a certain location there was something interesting in the image data, but not quite discernable because the image was recorded using a low resolution processing configuration. The next pass at that location, the fault management system **505** can select a configuration for higher resolution processing, so more detail is obtained.

Another input is a feedback loop **540** that monitors the output data **545** of the reconfigurable processing system **510**. For example, the fault management system **505** can include a detector (not shown) that receives and analyzes the output data **545** for certain characteristics. Based on those characteristics, the fault management system **505** selects a configuration. For example, the reconfigurable processing system **510** can be processing hyperspectral image data. Based on the output data, there can be particular wavelengths or wavelength bands that are of interest (e.g., show something

unexpected). Based on that, the fault management system **505** can reconfigure the reconfigurable processing system **510** to focus on those wavelengths of interest. The output data **545** can also indicate certain characteristics of the reconfigurable processing system **510** itself. Based on one or more of those characteristics, the fault management system **505** can reconfigure the reconfigurable processing system **510** based on some cost function. For example, one characteristic can be the measured performance in terms of work done (e.g., MIPS, bandwidth, memory utilization, etc.). Another characteristic can be a measure of the actual power consumed by the system **510**. Another characteristic can be the present health of the system **510**.

FIG. 6 illustrates a system **600** that for reconfigurable environmentally adaptive computing that uses multiple inputs. The system **600** includes a configuration controller system **605** and a reconfigurable image processing system **610**. The configurations from which the configuration controller system **605** can select are levels of compression of the image data, and include lossless, lossy, and very lossy. One input is the state of a solid state recorder **615**. The states can be, for example, nearly empty or nearly full. Another input is the state of a SEU alarm **620**. The states can be, for example, low or high, with high indicating the exceeding of a maximum threshold of particles. Another input is a GPS **625**, indicating an accurate location. Another input is the monitoring of the image data **630** to determine an environmental event represented in the data **630**. Based on the states of these inputs, the configuration control system **605** determines a configuration **635** (e.g., lossless, lossy, and very lossy) and transmits the configuration to the reconfigurable image processing system **610**. Table 2 shows a portion of a selection table that the configuration control system **605** uses to determine the configuration **635**.

TABLE 2

Hyperspectral Imager (630)	GPS (625)	SEU Alarm (620)	Solid State Recorder (615)	Compression Type (635)
Chemical Vapor Plume	Baghdad	Low	Nearly Empty	Lossless or None
Noisy Data	Any	High	Any	Very Lossy
Arctic Tundra	Northern Canada	Any	Nearly Full	Lossy
Hurricane	Caribbean	Low	Nearly Empty	Lossless or None

FIG. 7 is a block diagram of another exemplary reconfigurable environmentally adaptive computing system **700** that processes image data. System **700** captures image data using a video camera **703** and a video interface board **706**. The video interface board **706** includes a national standards television committee (NTSC) video interface **709**, an analog-to-digital converter (ADC) **712**, and a non-persistent storage module **715** (e.g., dual port video random access memory (RAM)). In capturing the image data, the NTSC video interface **709** receives an analog signal from the video camera **703** and transmits that analog signal representing the raw image to the ADC **712** for conversion into a digital format (e.g., logical ones and zeros). The raw image data, in digital format, is temporarily stored in the memory module **715** until the video interface board **706** can transmit the digital image data to a reconfigurable FPGA **718** for processing. The reconfigurable FPGA **718** can be implemented using, for example, a Xilinx® Virtex-II family FPGA (e.g., P/N 2V100 FG 256 BGA) manufactured by Xilinx, Inc. of San Jose, Calif.

To process the image data, the FPGA **718** includes a reconfigurable wavelet transform module **721**. A wavelet transformation is a two-parameter expression of a signal in terms of wavelet basis functions. System **700** includes three configurations of the wavelet transform module **721** corresponding to lossless compression, lossy compression, and very lossy compression. The lossless compression configuration implements a 5/3 wavelet transform. The lossy compression configuration implements a 9/7 wavelet transform using high-precision fixed-point wavelet coefficients. The very lossy compression configuration implements a 9/7 wavelet transform using low-precision fixed-point wavelet coefficients.

One of these three configurations is selected by a master configuration controller module **724**. The controller module **724** is also included in the FPGA **718**. The controller module **724** selects a configuration based on the input from two detectors, a SEU alarm **727**, and a GPS receiver **730**. The SEU alarm **727** includes a mini scintillator **733**, a photodiode **736**, a preamp/discriminator module **739**, and a counter/alarm circuit **742**. Similar to the examples above, the SEU alarm **727** monitors particles in the environment that can cause a SEU and outputs a signal to indicate whether a certain threshold has been exceeded, indicating a increased probability of a SEU. The SEU alarm **727** outputs to the FPGA an alarm signal with two states, a low state, indicating the threshold has not been reached, and a high state, indicating a threshold has been reached. The GPS receiver **730** calculates a location and sends the location data to the FPGA **718**.

TABLE 3

SEU Alarm State	Camera/GPS Receiver State	2D Wavelet Transform
Low	Camera pointing at a target of interest	5/3 Lossless
Low	Target of interest outside of camera field of vision (FOV)	9/7 Lossy
High	Any	9/7 Very Lossy

Table 3 shows an exemplary selection table used by the controller module **724** to select a configuration for the wavelet transform module **721**. As shown, when the output signal of the SEU alarm **727** is in a low state, the controller module **724** uses the GPS data to determine whether the compression configuration should be lossless or lossy. When the camera **703** is pointing at a target of interest, then the controller module **724** selects a lossless compression. To make the determination of whether the camera is pointed at a target of interest, the controller module **724** can have, for example, a list of location coordinates that indicate the camera is pointing at a target of interest. In this example, the controller module **724** compares the location coordinates from the list to the received coordinates, and if there is a match (or the coordinates are within a listed range), then the camera is pointing to a target of interest. When the camera **703** is not pointing at a target of interest, then the controller module **724** selects a lossy compression. When the output signal of the SEU alarm **727** is in a high state, the controller module **724** selects the very lossy compression, regardless of the coordinates received from the GPS receiver **730**. With the potential for poor quality data due to the high SEU rates, the controller module **724** minimizes resources used during this state.

In one example, the FPGA **718** is a partially reconfigurable FPGA, so that the wavelet transform module **721** can be reconfigured while the other modules (e.g., **724**, **751**, **754**,

757, etc.) also implemented in FPGA 718 remain intact. In another example the FPGA 718 is physically implemented using several FPGA chips, with different modules implemented in different FPGA chips. For examples using one or more Xilinx® FPGAs, Xilinx® Inc. also manufactures a system advanced configuration environment (System ACE) solution that includes a storage module 745 and a controller chip 748. The storage module 745 is a persistent memory device (e.g., flash memory) that stores all of the configuration data for the one or more FPGAs used to implement the FPGA 718. The controller chip 748 has the control logic to obtain the requested configuration data (e.g., from configuration controller module 724) and directed that selected configuration data stream accordingly. The FPGA 718 includes a system ACE interface module 751 to communicate with the controller chip 748.

The SEU alarm 727 and the video interface board 706 communicate with the FPGA 718 using a serial differential bus, such as RS-422 or low voltage differential signaling (LVDS). The signals from the SEU alarm 727 and the video interface board 706 are received by a RS-422/LVDS input interface module 754. The FPGA 718 also includes a RS-422/LVDS output interface module 757. The GPS receiver 730 communicates with the FPGA 718 via a joint test action group (JTAG) universal asynchronous receiver/transmitter (UART) interface module 760. The FPGA 718 can also communication with other modules in the system 700 through a RS-232 serial port 763.

The FPGA 718 also includes a direct memory access (DMA) controller module 766 that enables the on-the-chip-peripheral bus (OPB) 772 and the hyperspectral imaging (HSI) input bus 775 to directly access an external memory module, such as memory module 769. The FPGA 718 also includes a video graphics array (VGA) interface module 778 to transmit the digital image data to a digital-to-analog converter (DAC) module 785. The DAC 785 produces a VGA compliant output 788 that can be displayed on a VGA monitor.

The examples above list some exemplary applications for a reconfigurable, environmentally adaptive computing system. Other example applications can include, but are not limited to, the following examples: autonomous radiation protection for image processors in hostile environments; dynamically tunable image compression based on geographic location, target priority, and/or data quality for surveillance or medical diagnostics; adaptive beam forming and filtering for communications, sonar, radar, and other high-bandwidth interferometry applications; adaptive networking and cueing for sensor arrays based on external inputs such as device diagnostics, features of datastreams, or geographic location; autopilot and collision avoidance in hostile environments (e.g., underwater, low-visibility etc.); near real-time matched filtering, automatic target recognition, and object-level change detection for high-bandwidth remote sensors; and data fusion engines for multi-sensor suites.

The above-described techniques can be implemented in digital electronic circuitry, or in computer hardware, firmware, software, or in combinations of them. The implementation can be as a computer program product, i.e., a computer program tangibly embodied in an information carrier, e.g., in a machine-readable storage device or in a propagated signal, for execution by, or to control the operation of, data processing apparatus, e.g., a programmable processor, a computer, or multiple computers. A computer program can be written in any form of programming language, including compiled or interpreted languages, and it can be deployed in

any form, including as a stand-alone program or as a module, component, subroutine, or other unit suitable for use in a computing environment. A computer program can be deployed to be executed on one computer or on multiple computers at one site or distributed across multiple sites and interconnected by a communication network.

Method steps can be performed by one or more programmable processors executing a computer program to perform functions of the invention by operating on input data and generating output. Method steps can also be performed by, and apparatus can be implemented as, special purpose logic circuitry, e.g., an FPGA (field programmable gate array) or an ASIC (application-specific integrated circuit). Modules can refer to portions of the computer program and/or the processor/special circuitry that implements that functionality.

Processors suitable for the execution of a computer program include, by way of example, both general and special purpose microprocessors, and any one or more processors of any kind of digital computer. Generally, a processor will receive instructions and data from a read-only memory or a random access memory or both. The essential elements of a computer are a processor for executing instructions and one or more memory devices for storing instructions and data. Generally, a computer will also include, or be operatively coupled to receive data from or transfer data to, or both, one or more mass storage devices for storing data, e.g., magnetic, magneto-optical disks, or optical disks. Data transmission and instructions can also occur over a communications network. Information carriers suitable for embodying computer program instructions and data include all forms of non-volatile memory, including by way of example semiconductor memory devices, e.g., EPROM, EEPROM, and flash memory devices; magnetic disks, e.g., internal hard disks or removable disks; magneto-optical disks; and CD-ROM and DVD-ROM disks. The processor and the memory can be supplemented by, or incorporated in special purpose logic circuitry.

To provide for interaction with a user, the above described techniques can be implemented on a computer having a display device, e.g., a CRT (cathode ray tube) or LCD (liquid crystal display) monitor, for displaying information to the user and a keyboard and a pointing device, e.g., a mouse or a trackball, by which the user can provide input to the computer (e.g., interact with a user interface element). Other kinds of devices can be used to provide for interaction with a user as well; for example, feedback provided to the user can be any form of sensory feedback, e.g., visual feedback, auditory feedback, or tactile feedback; and input from the user can be received in any form, including acoustic, speech, or tactile input.

The invention has been described in terms of particular embodiments. The alternatives described herein are examples for illustration only and not to limit the alternatives in any way. The steps of the invention can be performed in a different order and still achieve desirable results. Other embodiments are within the scope of the following claims.

What is claimed is:

1. An adaptive computing system comprising:
 - a detector that generates an environmental signal representative of an external environmental condition;
 - a controller element that receives the environmental signal from the detector and selects a processing configuration from a plurality of processing configurations based on the environmental signal, the plurality of processing configurations comprising a first configura-

13

tion and a second configuration that is different from the first configuration, the second configuration being more reliable than the first configuration, more redundant than the first configuration, higher powered than the first configuration, or any combination thereof; and a processing element that reconfigures its programmable logic to change the way input signals are processed in accordance with the selected processing configuration received from the controller.

2. The adaptive computing system of claim 1, wherein the detector comprises a sensor.

3. The adaptive computing system of claim 2, wherein the sensor comprises a radiation detector.

4. The adaptive computing system of claim 3, wherein the radiation detector comprises a scintillator and a photo-diode.

5. The adaptive computing system of claim 2, wherein the sensor comprises a location detector.

6. The adaptive computing system of claim 5, wherein the location detector comprises a geographical positioning system sensor.

7. The adaptive computing system of claim 1, wherein the detector comprises a single event upset detection circuit comprising a radiation detector.

8. The adaptive computing system of claim 1, wherein the detector comprises a radiation detector and a location detector.

9. The adaptive computing system of claim 1, wherein the detector comprises an image processing detection circuit.

10. The adaptive computing system of claim 9, wherein the environmental signal is based on a characteristic of a processed image.

11. The adaptive computing system of claim 10, wherein the characteristic comprises a particular feature within the processed image.

12. The adaptive computing system of claim 10, wherein the characteristic comprises an unexpected feature within the processed image.

13. The adaptive computing system of claim 1, wherein the processing element comprises a programmable logic device.

14. The adaptive computing system of claim 13, wherein the programmable logic device comprises a field programmable gate array.

15. The adaptive computing system of claim 1, wherein the processing element comprises a radiation-hardened programmable logic device.

16. The adaptive computing system of claim 1, wherein the environmental signal is based on a characteristic of output data from the processing element.

17. The adaptive computing system of claim 1, wherein the processing element can accommodate high bandwidth applications.

18. A method comprising:
 receiving an environmental signal representative of an external environmental condition;
 selecting a processing configuration from a plurality of processing configurations based on the environmental signal, the plurality of processing configurations comprising a first configuration and a second configuration that is different from the first configuration, the second configuration being more reliable than the first configuration, more redundant than the first configuration, higher powered than the first configuration, or any combination thereof; and
 reconfiguring a programmable logic of a processing element to change the way input signals are processed according to the selected processing configuration.

14

19. The method of claim 18, further comprising:
 detecting the external environmental condition; and
 generating the environmental signal based on the detected condition.

20. The method of claim 19, wherein detecting comprises detecting a radiation level.

21. The method of claim 20, wherein the processing configuration is a first processing configuration, the method further comprising:
 detecting an increase in the radiation level, and
 selecting a second processing configuration that is more fault tolerant than the first processing configuration.

22. The method of claim 19, wherein detecting comprises detecting a position.

23. The method of claim 19, wherein detecting comprises detecting a particular condition within image data.

24. The method of claim 23, wherein detecting comprises detecting a particular feature within the image data.

25. The method of claim 23, wherein detecting comprises detecting an unexpected feature within the image data.

26. A computer program product, tangibly embodied in a computer and/or a removable storage medium, for reconfigurable environmentally adaptive computing, the computer program product including instructions stored on a computer readable medium, which when executed by a computer, causing an apparatus to:
 receive an environmental signal that represents an environmental condition external to the adaptive computing system;
 select a processing configuration from a plurality of processing configurations based on the environmental signal, the plurality of processing configurations comprising a first configuration and a second configuration that is different from the first configuration, the second configuration being more reliable than the first configuration, more redundant than the first configuration, higher powered than the first configuration, or any combination thereof; and
 initiate the reconfiguring of a programmable logic of a reconfigurable processing element to change the way input signals are processed according to the selected processing configuration.

27. An adaptive computing system comprising:
 a means for generating an environmental condition signal;
 a means for selecting a processing configuration from a plurality of processing configurations based on the environmental condition signal, the plurality of processing configurations comprising a first configuration and a second configuration that is different from the first configuration, the second configuration being a reliable than the first configuration, more redundant than the first configuration, higher powered than the first configuration, or any combination thereof; and
 a means for reconfiguring a programmable logic of a processing element to change the way input signals are processed according to the selected processing configuration.

28. The adaptive computing system of claim 1, wherein the plurality of processing configurations further comprises a third configuration that is different from the first and second configurations, the third configuration being more reliable than the first or second configuration, more redundant than the first or second configuration, higher powered than the first or second configuration, or any combination thereof.

15

29. The adaptive computing system of claim 1, wherein the external environmental condition represents an unscheduled change.

30. A method comprising:
 receiving a first environmental signal representative of a 5
 first external environmental condition;
 operating according to a first processing configuration
 corresponding to the first external environmental condition;
 receiving a second environmental signal representative of 10
 a second external environmental condition, the second
 external environmental condition being different from
 the first external environmental condition;
 selecting a second processing configuration correspond-
 ing to the second external environmental condition, the 15
 second processing configuration being different from

16

the first processing configuration, wherein the second processing configuration is more reliable than the first processing configuration, more redundant than the first processing configuration, higher powered than the first processing configuration, or any combination thereof;
 reconfiguring a programmable logic of a processing element to change the way input signals are processed according to the second processing configuration; and
 operating according to the second processing configuration.

31. The method of claim 30, wherein the second external environmental configuration is more harsh than the first external environmental configuration.

* * * * *